

User Manual


**Kinetic Wall Switch On/Off Receivers,
Kinetic Slim Grid Switch & Switch Frame**

TS 44552 - contains 40038 + 42499 + 42495

Important note: Isolate power before connecting receiver. Failure to do so can cause electric shock, fire or other hazards.


For your safety, this product must be installed in accordance with local Building Regulations. If in any doubt, or where required by the law, consult a competent person who is registered with an electrical self-certification scheme. Further information is available online or from your Local Authority.

A.40038 - What is in the box?



B. 40038 - Specifications

Dimensions:



Product Code:

RF KR01-ND-RF
RF & Wif KR01-ND-WF

Dimming:

N/A

Power:

300W LED (800W Resistive loads)

Input Voltage:

AC100 ~ 260V 50/60Hz

Radio Frequency:


RF 433MHz;
WiFi 2.4G for Smart Versions.

IP Rating:


IP20; Indoor use only.



C. 40038 - Functions of parts



D. 40038 - Wiring Diagram




E. 40038 - Installations


(a) Disconnect the mains before installation




Installation must be carried out by licensed electricians.



(b) Fix the cables to the receiver firmly.




(c) Press the Pairing Key to pair to switches.




to be continued
in pairing section

(d) Fix the receiver by screws or sticker provided.




F. 40038 - Pairing with Kinetic Switch

1. Pairing to kinetic switch - Standard method





Press the Pairing Key for 3-4s, until the RED indicator flashes slowly.




Whilst the indicator on the receiver flashes, press the Kinetic switch ONCE to complete the pairing.

2. Pairing to kinetic switch - Remote pairing to installed receiver.


(a) Turn on the light



(b) Press 8 times on Paired Switch within 3s




(c) Receiver enters a Switch Pairing window



Light: Slowly On/Off flashes

(d) Press the key of unpaired switch ONCE to complete the pairing.



Once


Unpaired Switch




G. 40038 - Un-pairing

(a) Kinetic Switch

Un-pairing from receiver




H. 40038 - Pairing Limitations



Max. 10 Kinetic Switches to pair ONE On/Off Receiver


To avoid sync problem, we DO NOT suggest to pair multiple On/Off receivers to one or multiple Kinetic Switches.

I. 40038 - Control the On/Off Receiver via Kinetic Switch





J. 40038 - Attention

d = Min. 50mm




Do not cover with insulation




A. 42499+42495 - What is in the box ?

1 Gang




x 1

KSMK-1G



x 1


Frame



KFMK-01

B. 42499+42495 - Specifications And Installations

Dimensions:



Power Source:

Self Powered (Kinetic)

IP Rating:

IP20

Transmission Range:

Outdoor 80m (no barrier)

Radio Frequency:

433 MHz

Body Material:

Polycarbonate

Indoor 40m (plaster board; drywall)

Switching Type:

Push Switch

Weight:

24g

Indoor 30m (concrete, glass walls)

Dimming Type:

Push Selected


(Range may vary depending on surrounding situation)



Install on or close to metal surface would decrease the transmission range significantly. Suggest to keep away from metal surface at least 1m to get the best performance.




C. 42499+42495 - Compatible Receiver




ON / OFF Receiver

D. 42499+42495 - Operation

1 Gang



ON / OFF Switch




Single press to
turn on / off


E. 42499+42495 - Pairing with Receiver

Pairing to Receiver - Standard method

(a)



(b)




Press the Pairing Key for 3-4s,
until the RED indicator flash slowly.



While the indicator on receiver flashes,
press the Kinetic switch ONCE to complete the pairing.

F. 42499+42495 - Installation

Installation 1:



Antenna Installation



Arrow pointing upwards

Helpline

If you receive this item with parts broken or missing,

please telephone: **0333 0050077**

Please have ready your name, address, tel. no.,
product reference, where purchased and parts required.
An answering service is in operation outside office hours
and during busy periods.

**We regret that we are unable to give advice on
internal house wiring.**

Cascade Holdings Ltd, Gorse Mill, Gorse Street,
Chadderton, Oldham. OL9 9RJ
www.cascadehl.com/#contact

EU Authorised Representative: Authorised Rep Compliance,
Ground Floor, 71 Lower Baggot Street, Dublin, Ireland,
D02P593.
www.authorisedrepcompliance.com



This product should be disposed of responsibly at the end of its life.
Please recycle where facilities exist. Check with your Local Authority
or retailer for recycling advice.
(Waste Electrical and Electronic Equipment Directive)

**UK
CA** **CE**